

[View Whistler Classic Linear on website](#)

[View application photos](#)



**WATT/CCT**  
FIELD-ADJUSTABLE

## PRODUCT DESCRIPTION


**Whistler Classic Direct-Indirect Linear Field**  
Wattage & Kelvin temp selectable. Length: 2', 4', 8' width 3.4" with different connector built different shapes, can be widely used indoor (damp locations) Excellent for hospitals, schools, office, shops, restaurants, storage rooms, supermarkets, etc.




### TOP FEATURES

- 115-120 lm/W
- Field-adjustable Power and CCT.
- Direct-Indirect flux ratio adjustable.
- Continuous run available.
- Multiple connection method.
- 12Vdc auxiliary
- Motion Sensor Control Available (Option)

### Dimensions



### Distributions



## SPECIFICATION

TYPE	SB-OL2FT10121620W27-5CCT-W-G2	SB-OL4FT20243240W27-5CCT-W-G2	SB-OL8FT40486480W27-5CCT-W-G2
WATTAGE	(2FT) 10W/12W/16W/20W	(4FT) 20W/24W/32W/40W	(8FT) 40W/48W/64W/80W
LUMEN	1100 lm/1400lm/1800lm/2300lm	2200 lm/2800lm/3600lm/4600lm	4400 lm/5600 lm/7200 lm/9200lm
EFFICACY	> 115 lm/W		
CCT	2700K/3000K/3500K/4000K/5000K		
DEFAULT SETTING	Maximum Power & 4000K, down light 100%, Up light off		
CRI	80		
INPUT VOLTAGE	AC120-277V		
LIGHT ANGLE (One-sided)	110°		
POWER FACTOR	0.90		
DRIVER EFFICACY	86%		
DIMMING	0-10V Dimming (12Vdc auxiliary dimming)		
WORKING TEMPERATURE	-4°F ~ 122°F		
LIFESPAN (L70)	100,000 hours		
PROTECTION LEVEL	Damp locations		
CABLE	5core, 18AWG 47.83 inch (SOLD SEPARATELY)		
WARRANTY	5 year limited		

**MODEL INFORMATION:**

**Example: SB-OL2FT10121620W W27-5CCT-W**

Products series	Size	Wattage	Voltage	Kelvin	Finish	Control
*SB-OL	*2FT	*10121620W= 10W/12W/16W/20W	*27=120-277V	*5CCT=2700K/ 3000K/3500K/ 4000K/5000K	*W=White (standard)	M=Motion Sensor
	4FT	20243240W= 20W/24W/32W/40W			D=Dark Bronze	E=Emergency
	8FT	40486480W= 40W/48W/64W/80W			B=Black S=Silver	EM= Emergency+Motion Sensor


**\*Please see page 3 for optional controls, page 4 for accessories, page 5 for modular options\*  
\*Accessories and Parts Sold Separately\***

**CONTROL MODULE:**



**DIMENSION:**

Unit: mm/inch



<b>WATTAGE</b>	10W/12W/16W/20W
<b>WEIGHT(G.W)</b>	3.63 lbs (1 pcs/carton)
<b>OUTER BOX</b>	25.78"X7.95"X7.44"(6 pcs/CTN)
<b>INNER BOX</b>	25.78"X2.48"X3.4"(1 pcs/CTN)

<b>WATTAGE</b>	20W/24W/32W/40W
<b>WEIGHT(G.W)</b>	6.60 lbs (1 pcs/carton)
<b>OUTER BOX</b>	49.40"X7.95"X7.44"(6 pcs/CTN)
<b>INNER BOX</b>	48.77"X2.48"X3.46"(1 pcs/CTN)

<b>WATTAGE</b>	40W/48W/64W/80W
<b>WEIGHT(G.W)</b>	13.20 lbs (1 pcs/carton)
<b>OUTER BOX</b>	97.48"X5.35"X8.07"(4 pcs/CTN)
<b>INNER BOX</b>	96.57"X2.48"X3.54"(1 pcs/CTN)

**OPTIONAL CONTROLS: (SOLD SEPARATELY)**

**EMERGENCY BACK-UP: (SOLD SEPARATELY)**



**(Available only for  
4FT and 8FT models)**


**SB-EMS8W27-XX**  
8W Emergency Backup Battery  
LED Driver

**SB-EMS15W27-XX**  
15W Emergency Backup Battery  
LED Driver

**SB-EMS20W27-XX**  
20W Emergency Backup  
Battery LED Driver

**CONTROL: (SOLD SEPARATELY)**

Unit:mm



**BRI810-B-D**  
Microwave Motion Sensor



**NLC-MW-SQ-005**  
Microwave Motion Sensor  
Note: Build in(Option)



**RC-100**  
Microwave Sensor Remote Controller  
Matching Sensor Model:  
**NLC-PIR-SQ-001,NLC-MW-SQ-005, BRI810-B-D**



**Bluetooth**  
**NLC-BT-PIR-SR-001**  
PIR Bluetooth Microwave Sensor  
For Silvair Systems  
**(Silvair Bluetooth )**



**NLC-PIR-SQ-001**  
Bi-Level PIR Infrared Sensor  
( DC 12V sensor installation box )




**Bluetooth**  
**NLC-BT-PIR-GE-001**  
PIR Bluetooth  
Microwave Sensor For GEBC Systems  
**(GEBC Bluetooth)**



**SB-OL-M-DC**  
DC Sensor Connection kit  
Matching Sensor Model:  
**NLC-PIR-SQ-001,NLC-BT-PIR-SR-001**  
(2FT,4FT,8FT)

**ACCESSORIES: (SOLD SEPARATELY)**



**SB-OL-ceiling install**  
Ceiling Install KIT  
Wire Rope Length:  
φ0.06X39.4-inch(2PCS)  
  
(2FT,4FT,8FT)




**SB-OL-5CPC-W**  
Five-core Power Cord  
Length: 47.83"  
  
(2FT,4FT,8FT)




**SB-OL-6CPC-W**  
Six-core Power Cord  
Length: 47.83"  
Note: Emergency Battery  
backup Inputs required  
  
(2FT,4FT,8FT)




**SB-OL-Canopy-M**  
Canopy for Motion Sensor Install  
  
(2FT,4FT,8FT)




**SB-OL-SMK-WMK-W**  
Wall and Surface Mounting KIT  
Wire Rope Length:φ0.04X4.7 inch (2PCS)  
Wire Length : 7.9 inches  
  
(2FT,4FT,8FT)




**SB-OL-T-Grid**  
T-grid Suspension Mount Bracket  
Wire Rope Length:φ0.06X39.4 inch (2PCS)  
  
(2FT,4FT,8FT)



**SB-2FT-OL-RMK-G2**  
Recessed Mounting Kit  
For 2FT Architecture Selectable  
LED Linear Light



**SB-4FT-OL-RMK-G2**  
Recessed Mounting Kit  
For 4FT Architecture Selectable  
LED Linear Light



**SB-8FT-OL-RMK-G2**  
Recessed Mounting Kit  
For 8FT Architecture Selectable  
LED Linear Light


**MOUNTING EXAMPLES: (SOLD SEPARATELY)**

**MOUNTING (SOLD SEPARATELY)**


Pendent mount, surface mount, wall mount,  
recessed mount are available with accessories(purchase separately).



**Pendent mount**



**Surface mount**



**Recessed mount**





**Wall mount**

**CONNECTION METHOD:**

**Fast and seamless connection**

Screw-free to remove end-cover. Tool-free press lock connection.



**MULTIPLE CONNECTION METHOD: (SOLD SEPARATELY)**

<p>"I" connecting with Straight shape connector (There is no need to add additional connectors, and the two ends of the lamp do not need to be screwed.)</p>	<p>SB-OL90-2T-G2 "L" connector</p>	<p>"L" connecting with 'L' shape connector</p>
<p>SB-OL90-3T-G2 "T" connector</p> <p>"T" connecting with 'T' shape connector</p>	<p>SB-OL90-4T-G2 "+++" connector</p>	<p>"+" connecting with '+' shape connector</p>


**Warning!** Each Power Feed: Total connected load is ≤500W at 120V and ≤1000W at 277V.




**PHOTOMETRICS:**

For complete IES files, please visit our website.

**SB-OL2FT10121620W27-5CCT-W-G2 (20W&4000K Down light 50%, Up light 50%)**



**SB-OL4FT20243240W27-5CCT-W-G2 (40W&4000K Down light 50%, Up light 50%)**



**SB-OL8FT40486480W27-5CCT-W-G2 (80W&4000K Down light 50%, Up light 50%)**

